

FutureCom™ EA Patch Cord, FRNC, RJ45 - RJ45 connector, crossed

red, 1 m

CORNING

The application-neutral FutureCom™ category 6_A patch cords have four individual foil-shielded pairs (PiMF) and an additional braid shield (S/FTP). They are assembled with a shielded RJ45 connectors on each end.

The zero halogen patch cords (LSZH) are non-corrosive according to IEC 60754-2 (FRNC) and EN 50267, low smoke according to IEC 61034 and EN 50268 and flame retardant according to IEC 60332-1, Category B and EN 50266-2-1. FutureCom™ S500 patch cords provide additional latch protection.

Pin Assignment: 1-3 / 2-6 / 3-1 / 4-7 / 5-8 / 6-2 / 7-4 / 8-5.

They are available in various lengths and colours.

Features

- S/FTP flex cable, Category 7
- Application-neutral due to using all four pairs of RJ45 connectors
- Minimum surface transfer impedance of cable (<10 mΩ/m at 10 MHz)
- Outstanding transmission characteristics according to 10GBase-T
- Additional latch protection
- Category 6_A
- Crossed version
- PVP Certificate



Specifications

General Specifications	
Cable Assembly Type	Patch Cords
Environment	Indoor
Cable Type	S/FTP
Halogen-free	Yes
Category	10GBase-T

Temperature Range	
Installation and Assembly	0 °C to 50 °C
Operation	-20 °C to 60 °C

FutureCom™ EA Patch Cord, FRNC, RJ45 - RJ45 connector, crossed

red, 1 m

CORNING

Design - Connector A

Connector Type	RJ45 - 8/8
----------------	------------

Mechanical Specifications - Connector A

Durability	750 Cycles
------------	------------

Electrical Specifications - Connector

Insulation Resistance	≥ 5000 MΩ
-----------------------	-----------

Design - Connector B

Copper Connector Type - B	RJ45 - 8/8
---------------------------	------------

Cable Design

Min. Bend Radius Installation	40 mm
Min. Bend Radius Operation	30 mm
Outer diameter	5.8 mm
Outer Jacket Material	LSZH™/FRNC
Outer Jacket Colour	red

Mechanical Characteristics

Copper conductor	AWG 26
Fire Load	0.43 MJ/m

Electrical characteristics (at 20°C)

DC resistance unbalance	290 %
Impedance Z_0 at 0-100 MHz	100 Ω +/- 15%
Impedance Z_0 at 101-250 MHz	100 Ω +/- 18%
Impedance z_0 at 251-600 MHz	100 Ω +/- 25%
Surface transfer impedance	< 10 mΩ/m per meter at 10 MHz
Mutual capacity	43 pF/m
Earth coupling at 0.001 MHz	1600

FutureCom™ EA Patch Cord, FRNC, RJ45 - RJ45 connector, crossed

red, 1 m



Electrical characteristics (at 20°C)

Propagation delay ≥ 10 MHz	4.3 ns/m
Delay skew	20 ns/100 m

Chemical characteristics

RoHS	Free of hazardous substances according to RoHS 2002/95/EG
------	---

Ordering Information

Part Number	CCAAGB-G5102-A010-C0
Product Description	FutureCom™ EA Patch Cord, FRNC, RJ45 - RJ45 connector, crossed, red, 1 m
EAN Code	4042673346135
Length	1 m

Shipping Information

Units per Delivery	1/1
--------------------	-----



Corning Optical Communications GmbH & Co. KG · Leipziger Strasse 121 · 10117 Berlin, GERMANY
00 800 2676 4641 · FAX: +49 30 5303 2335 · www.corning.com/opcomm/emea

A complete listing of the trademarks of Corning Optical Communications is available at www.corning.com/opcomm/emea/trademarks. Corning Optical Communications is ISO 9001 and ISO 14001 certified. © 2014 Corning Optical Communications. All rights reserved.